

Instructions for Targus Charger And AA Batteries

The following instructions apply to charging Targus batteries with the Targus Digital Charger. If using a different brand of charger, please follow those instructions.

IMPORTANT: *For maximum performance, we recommend charging your new batteries for at least 24 hours before initial use.*

1. To charge, insert the batteries into the charger unit so that the plus (+) and minus (-) terminals on the batteries match the markings on the charger unit. (Batteries may be inserted into the charger at any time, whether fully drained or not, and will be charged the appropriate amount.)
2. Plug the Charger unit into a standard 120V AC wall outlet.
3. A red light on the LED display will automatically come on, indicating that the batteries are charging. After 14-16 hours when charging is complete, the light on the LED display will remain red. You may now remove the fully charged batteries. (Batteries may also be removed prior to completion of charging, if necessary, without adversely impacting battery life. The length of operating time, however, will be shorter than if the batteries were fully charged.)
4. Batteries should not be left in the charger while plugged into the wall for more than 24 hours.
5. After charging is completed, unplug the charger from the wall outlet for storage.

General Information

1. Targus batteries can be recharged up to 1,000 times.
2. The Targus Digital Charger is designed to recharge only AA size rechargeable NiMH batteries. For best results, only use Rechargeable Targus batteries with the Targus Charger.

Tips for Maximum Battery Performance

1. New Targus batteries should be charged for at least 24 hours before initial use.
2. Fully charged Targus batteries will self-discharge by 1% to 2% per day. If your batteries have not been used in over one week, we recommend recharging them before use to get full run time.
3. NiMH AA batteries are fully charged in approximately 14-16 hours.
4. To achieve the longest operating time per charge, do not remove the batteries from the charger prior to the 14-16 hour charge time.

Troubleshooting

Should batteries not charge properly, or the batteries discharge quickly, please check the following:

1. For best results, only charge Targus batteries with the Targus Digital Charger.
2. Make certain batteries are facing in proper direction, as indicated in modules.
3. Check all batteries and Digital Charger to make sure contacts are clean.
4. If the LED does not illuminate, check to see if you have plugged the charger into an outlet that is "live."

One Year Limited Warranty

The Targus Digital Charger and 2200mAh rechargeable AA batteries are warranted to be free of defects from workmanship and materials when used under normal conditions for the period of one (1) year from the original date of purchase. Should our product fail to perform properly, we will repair or replace it at our option, free of charge. Purchaser is responsible for returning the product to the place of purchase. If that cannot be done reasonably, please write us stating the nature of the defect and the date of purchase and send, with your product, to www.targusdigital.com.

All associated freight and insurance costs are the responsibility of the purchaser. Targus will bear the cost of shipping the repaired or replaced item to you.

This warranty does not apply when:

- Repairs have been made or attempted by others
- Repairs are required because of normal wear and tear
- The product has been abused, misused or improperly maintained
- Alterations have been made to the product

This warranty excludes any liability other than that expressly stated above, including, but not limited to, any incidental or consequential damages.

This warranty provides the original purchaser with specific rights, which may vary from state to state. Some states do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation of damages may not apply to you. For information regarding these rights, please consult the applicable state laws.

Targus

Thank you for purchasing a Targus product. To ensure safe use and maximum performance from your Targus Digital Charger and Targus batteries please read these instructions carefully and keep them for future reference.

Important Safety Precautions

1. For dry, indoor use only. Do not use Targus Digital Charger outdoors or expose to moisture.
2. Do not incinerate or mutilate batteries. Such treatment could cause cells to burst open and/or release toxic material.
3. Do not touch the charging terminals with any conductive material. Avoid storing batteries in a container with other metal objects such as nails or coins, and do not expose batteries to water or rain. Such circumstances can result in short-circuiting, which could cause current flow, overheating and burns.
4. The Targus Digital Charger is designed for rechargeable Nickel Metal Hydride (NiMH) batteries *only*. Do not charge batteries other than rechargeable NiMH. Explosion may result.
5. Do not charge Alkaline, Carbon Zinc, Lithium or any other type of rechargeable, non-rechargeable or disposable batteries. These batteries may rupture, leak or explode, resulting in personal injury and/or property damage.